


移動電源型號：YN-050M

用戶手冊


感謝您使用YN-050M移動電源

本產品適合為絕大部分DC-5V的通訊及數碼產品充電



產品介紹

1.本產品是由一個USB-C口，2個USB-A口，一個Lightning口，一個手電筒，一個按鍵組成。



2.電量指示：本產品帶1個數碼管顯示屏，便於您對移動電源掌控，按一下按鍵，可顯示當前電量狀態。



3.按鍵功能：单击打开输出；双击打开手电筒，双击关闭手电筒；长按3秒，LO显示绿色，表示打开小电流模式，再长按3秒，LO绿灯关闭，小电流模式关闭。

給設備和手機充電

1.45W PD輸出，支持PD設備充電.如MACBOOK、iPhone、iPad等智能手機快充。

2.根據不同的手機和設備選擇USB線。

給移動電源充電

1.本產品支持USB-C口、Lightning口給移動電源充電。（如圖2/3）




圖2：USB-C口給移動電源充電




圖3：Lightning口給移動電源充電

2.不同的充電器給移動電源充滿時間不一樣，使用30W充电器最快3-4小時充滿整個移動電源。

注意事項

- 1.因本品容量較大，採用快充充電器，為其充滿最快需3-4小時左右，具體請以實際為準。
- 2.若使用本品給用電設備充電時出現不能充電，請檢查接線是否正常，牢固.充電接口配件是否合適，建議選用隨機附送配件或正規品牌電源適配器與充電線為其充電。
- 3.移動電源存在轉換效率，故移動電源容量不等同於可充電量。
- 4.本移動電源適合給絕大部分手機充電，會出現不支持個別型號手機充電。
- 5.建議至少每6個月內為其完成一次完全充電。

儲存與工作溫度

儲存與工作溫度（為保護電池與延長電池壽命.盡可能在電池的正常溫度範圍內使用.熱量最容易降低電池的效能）

儲存溫度:-5~+35℃(小於一個月),-5~+30℃(小於六個月)

工作溫度:充電:0~+45℃;放電:-20~+60℃

安全說明

警告:不遵循這些安全說明可能會導致起火.觸電.損壞或其他傷害.



選用高品質鋰電池與優質芯片，請放心使用

- 1.請不要擅自拆卸本產品，不要將產品放入高溫處或投入火中，否則會有燃燒或爆炸危險。
- 2.請勿靠近易燃物品及在陽光下暴曬。
- 3.請勿與堅硬的物體相撞擊。
- 4.如果發現本品有鼓脹等明顯不良現象或被充電設備有鼓脹等其他明顯不良現象，請用戶停止使用本產品。
- 5.此設備不適用於生理、感知和心智能力低下的人士（包括兒童），除非有專門負責他們人身安全的人士監督或指導他們使用.應當看管好小孩，以確保他們不將此當玩具來玩。

技術規格

電池類型: 18650
容量: 3.6V @20000mAh/72Wh
輸入:
Lightning: DC 5V/3A DC 9V/2A
USB-C: DC 5V/3A 9V/3A 12V/2.5A 15V/2A 20V/1.5A
輸出:
USB-C: (45W PD) DC 5V/3A 9V/3A 12V/3A 15V/3A 20V/2.25A (PPS: 3.3V-11V/3A)
USB-A 1-2: DC 4.5V/5A 5V/4.5A 9V/2A 12V/1.5A
尺寸: 170*80*21.6mm
重量: 460g
顏色: White Black Blue

產品清單

移動電源*1 PCS
充電線*1 PCS
說明書*1 PCS
保修卡*1 PCS

保修卡

本產品為客戶提供自購買之日起12個月內的保修服務

保障條件:需要保修服務時.請出示本保修卡.並請詳細填寫相關內容.本公司向產品用戶提供從產品購買之日起12個月的保質期。

保修範圍:

- 1.在正常使用的狀態下出現產品質量問題。
- 2.如因操作失誤造成對產品的損害.不在保修範圍。
- 3.自行拆機後.不予保修。
- 4.標貼撕毀的機器.不予保修。

不在保修範圍內的產品.我司可提供維修服務.維修費用需由客戶承擔。


		客戶姓名	
購買日期		聯繫電話	
電子郵箱			
客戶地址			
產品異常現象描述			

Powerbank Model: YN-050M

User Manual


Thanks for choosing YN-050M power bank model

This model compatible with most DC 5V/9V devices



Product presentation

1. Built-in Dual USB-A Ports, One Lightning Port, One USB-C Port and one Flashlight.



2. Power indicator light: Digital display shows the current battery level.



3. Button Function: Single Click to Open the Output function. Double Click to turn on the flashlight, Then double click to turn off the flashlight.


Charge mobile phone devices

1. 45W PD Out, Support devices with PD charging. Such as Macbook/ iPhone/ iPad and other Phone models.


2. Choose different USB charging cable according to different mobile phone and devices.

Recharge Power Bank

1. This model Supports USB-C/ Lightning Port Input charging.



(1) USB-C Port to recharge the power bank



(3) Lightning Port to recharge the power bank

2. Different chargers take different amounts of time to fully charges this model. If use a 30W charger to charge the power bank, it will take about 3-4 hours to fully recharged the power bank.

Attentions

1. Cause the high battery capacity of this model, it is recommended to use the fast charging adapter to charge the power bank.
2. If the power bank can't supply power to devices, Please check the devices connected or not, Confirm Whether you choose the right cable. Suggest using original adapter and cable accessories.
3. As the power bank has conversion rate, so the battery capacity is not the real capacity you can use.
4. It is recommended to complete a full charge at least every 6 months

Storage and working temperature

Storage and working temperature (Please use it during the normal temperature in order to protect the battery life)

Storage temperature: -5~ +35℃ (Less than one month) -5 ~+30℃ (Less than 6 months)

Working temperature: Charging 0~+45℃ . discharging -20~+60℃

safety instructions

Warning: If don't follow safety instructions, maybe cause a fire, some breakdown or other damages



Choose high-quality lithium cells and high-quality chips, please rest assured to use it

1. Don't disassemble this model by yourself. Do not put the product into a high temperature or fire, or it will burn Or explosion hazard.
2. Keep The power bank away from flammable materials and exposure to sunlight.
3. Do not collide with hard objects.
4. If it is found that the product has obvious adverse phenomena, Please stop using this product.
5. Keep out of the hands of children.

Specification

Battery Type: 18650
Capacity: 3.6V @20000mAh/72Wh
Input:
Lightning: DC 5V/3A DC 9V/2A
USB-C: DC 5V/3A 9V/3A 12V/2.5A 15V/2A 20V/1.5A
Output:
USB-C: (45W PD) DC 5V/3A 9V/3A 12V/3A 15V/3A 20V/2.25A (PPS: 3.3V-11V/3A)
USB-A 1-2: DC 4.5V/5A 5V/4.5A 9V/2A 12V/1.5A
Size: 170*80*21.6mm
Weight: 460g
Color: White Black Blue

Accessories

Power bank
Cable
C-C PD Cable

Warranty Card

The warranty time is one year

Warranty Policy

Please show your warranty card when you need warranty services, and fill in the relevant information ,we offer one year warranty time.

Scope of warranty :

1. The failure of a product under normal use

Even if within the warranty period, if the following occurs, certain maintenance costs will be charged.

1. The malfunction and damaged caused by incorrect use ,the unauthorized repairs and alteration.
2. Products tags are tear up.

Model		Name	
Purchase Data		Contact Number	
Email			
Address			
Anomaly Product description			